

Product Data Sheet



Scout

Fortified's Scout redefines versatility. Inspired by our Fortress, Scout allows for live monitoring, cloud access, live alerts, a communication system, and is linkable to our Fortress as needed. Scout is designed for placement in any environment or sized project while being fully scalable.

Scout integrates with Fortified's Gatekeeper and Overwatch solutions. Gatekeeper is advanced RFID tracking technology. RFID readers can be deployed and workers can be tracked through a simple sticker affixed to their hardhat. Simply walk by the Scout reader for time & attendance. No badging. No Lines. Overwatch allows for easy placement of cameras around a jobsite connected back to Scout for 24/7 access to camera streams.

FEATURES AND BENEFITS

- Cloud connectivity via 4G/5G modem
- Any Scout can support up to 4 cameras, or 3 cameras & 1 RFID reader (up to 4 antennas)
- Global accessibility by project team members
- Standard 120v AC power required, solar and battery backup available upon request
- Event trigger 100 watt loud speaker and strobe light



*Scout shown with optional Gatekeeper
RFID reader*

ADD ON FEATURES— GATEKEEPER

- Manpower attendance reporting
- Comms— SMS text, call, or PA
- Instant comms to all workers or a foreman

ADD ON FEATURES— OVERWATCH

- Optical fencing with smart detection analytics
- Live monitored 24/7/365 with one way communication for stand down or alerts
- User programmable schedule and arming with independent system control as needed
- Visual progress reporting via timelapse

Fortified

5353 Main Street, Suite 150 - Williamsville, NY 14221

(833) 310-1554 - fortifiedinc.com

Scout

SPECIFICATIONS:

Power: 120v AC in, solar or battery backup options available upon request

Operating Temperatures: -20F to 120F

Camera Configuration: Bullet or Turret cameras, IR or BI Spectrum available

Lighting: Additional relay boards and flood lighting available upon request

Speaker: 100 watt

Strobe: 1 multi-color upon alarm

Communications: Dual SIM service router with failover if required (Verizon and AT&T unless specified)

Wireless Frequencies: 2.4 GHz, 5 GHz, and 345 & 900 MHz

GPS Enabled: Yes

Fortified ARC Link with 24/7 Monitoring: Yes

Additional UL Monitoring if needed: Yes

DEPLOYMENT:

Scouts come with four (4) mounting brackets and hardware to affix the brackets to the unit. Open the door and secure the bracket to the Scout using the available through-holes.

Each Scout should be secured with user-supplied screws, bolts, etc. given the type of substrate the Scout is affixed to.

Fortified recommends using hardware approximately the same size as the through-holes provided (approximately 1/4"). Fortified is not liable for the manner in which a Scout and its affiliated devices (if applicable) are installed.

Cameras, RFID readers, Solar Panels and other attached devices should be mounted based on best practices and field coordinated with the GC, developer, or appropriate project manager.

If in doubt, please contact Fortified.

LEADTIME & ORDERING:

7 to 10 days based on volume

(833) 310-1554

